



The manufacturer  
may use the mark:



Revision 4.2 June 25, 2025  
Surveillance Audit Due  
April 1, 2028



# Certificate / Certificat Zertifikat / 合格証

AUT 1108054 C002

*exida* hereby confirms that the:

## **AutroFlame X33AF, X32AF Multispectrum IR Flame Detectors**

### **Autronica Fire and Security AS Trondheim, Norway**

Have been assessed per the relevant requirements of:

**IEC 61508 : 2010 Parts 1-3**

and meet requirements providing a level of integrity to:

**Systematic Capability: SC 2 (SIL 2 Capable)**

**Random Capability: Type B Element**

**SIL 2 @ HFT=0; Route 1<sub>H</sub>**

**PFD<sub>AVG</sub> and Architecture Constraints  
must be verified for each application**

#### **Safety Function:**

The Multispectrum IR Flame Detector will sense infrared emission from flame sources and signal the 4 –20 mA output or relay output to indicate the potentially dangerous condition.

#### **Application Restrictions:**

The unit must be properly designed into a Safety Instrumented Function per the Safety Manual requirements.



*Molly Lynn O'Brien*

Evaluating Assessor

*Robert E. L. Smith*

Certifying Assessor

AUT 1108054 C002

**Systematic Capability: SC 2 (SIL 2 Capable)****Random Capability: Type B Element****SIL 2 @ HFT=0; Route 1<sub>H</sub>****PFD<sub>AVG</sub> and Architecture Constraints  
must be verified for each application****AutroFlame X33AF,  
X32AF Multispectrum  
IR Flame Detectors****Systematic Capability:**

The Product has met manufacturer design process requirements of Safety Integrity Level (SIL) 2. These are intended to achieve sufficient integrity against systematic errors of design by the manufacturer.

A Safety Instrumented Function (SIF) designed with this product must not be used at a SIL level higher than stated.

**Random Capability:**

The SIL limit imposed by the Architectural Constraints must be met for each element.

**IEC 61508 Failure Rates in FIT\***

Device	$\lambda_{SD}$	$\lambda_{SU}$	$\lambda_{DD}$	$\lambda_{DU}$	SFF
X33AF/X32AF Relay Output, FW Rev E and F	335	120	556	88	92.0%
X33AF/X32AF 0-20 mA Output, FW Rev E and F	0	106	920	75	93.2%
X33AF/X32AF 0-20 mA Output with HART, FW Rev E and F	0	110	1146	93	93.1%

\* FIT = 1 failure / 10<sup>9</sup> hours

**SIL Verification:**

The Safety Integrity Level (SIL) of an entire Safety Instrumented Function (SIF) must be verified via a calculation of PFD<sub>AVG</sub> considering redundant architectures, proof test interval, proof test effectiveness, any automatic diagnostics, average repair time and the specific failure rates of all products included in the SIF. Each element must be checked to assure compliance with minimum hardware fault tolerance (HFT) requirements.

The following documents are a mandatory part of certification:

**Assessment Report:** DET 11-08-054 R004 V4 R2

**Safety Manual:** #95-8747, Rev 2.1 and later



80 N Main St  
Sellersville, PA 18960